2. SAFETY GUIDELINES AND MEASURES

2.1. Intended Use PLEASE FOLLOW THESE INSTRUCTIONS AND SAVE FOR FUTURE. LOOK

AT NEAR TO THE LITHIUM LIFEPO4 BATTERY.

The battery may only be used for the purposes described in the operating instructions. Use for other purposes is considered improper use and has the invalidity of the result in product guarantee. The manufacturer is not liable for damage caused by faulty, improper use or improper use of the product. Use in aviation or in medical devices that serve to support life contradict the intended use. LiFePO4 Batteries are designed for use as energy storage. Possible areas of application for the battery are used as a service and on-board

2.2. MARKINGS

C€ Conformity mark (CE mark).

WoHS RoHS Conformity according to RoHS directive.

Conformity mark for material safety data sheet.

Fire, naked flames and smoking are prohibited! Sparking when handling avoid cables and short circuits.

Not waterproof.

Dispose of the Lithium LiFePO4 battery in accordance with your local, state, and local authority, federal laws and regulations. Batteries can be sent to the manufacturer, can be returned. Do not mix with other (industrial) waste.

This product or parts of this product can be recycled.

The connections of the lithium battery are always live. Therefore, never place objects or tools on the lithium battery. Avoid short circuits. Use isolated tools. Do not wear metallic objects such as watches, bracelets, etc. on your body. Use at a class

D fire extinguisher, foam or CO2 fire extinguisher. 2.3. STORAGE AND TRANSPORT INFORMATION

The battery must be packed and protected well during transport. The lithium battery must be transported according to the rules for transport, these should

always be followed (transportation code UN3480/UN38.3).

Never lift the battery by the terminals, only by the handles.

The battery should be stored in temperatures from -10°C to +40°C. During transport, the battery should be about 50-60% charged.

The battery should be charged every three months to keep it active so that it always works maximum.

Batteries that are marked with the recycling symbol must be returned to approved

recycling points. You can also contact the manufacturer by arrangement to be returned. Batteries must not be disposed of in household or industrial waste.

2.5. IMPORTANTINSTRUCTIONS

Do not open the LiFePO4 battery without consulting the dealer. Unauthorized opening of the battery voids the manufacturer's warranty.

Only use the battery for the application for which it is intended.

- Do not short-circuit the LiFePO4 battery. The cable connections to the consumers
- must go through a backup to be protected.
- Installation and maintenance may only be carried out by qualified specialists.
 Do not expose to permanent direct sunlight. Protect from the effects of
- heat. Temperatures above +60 ° C can damage the battery. • Use only compatible chargers. The battery is in a longer storage of all

disconnect devices.

· Pay attention to proper assembly.

- Avoid damage of any kind, for example by failing, drilling, etc. (Risk of short circuit). Always keep the battery dry and clean.
- Note the plus (+) and minus (-) markings on the LiFePO4 battery and the device and
- pay attention to the correct polarity.
- . The cycle capacity may vary due to the change in the working temperature and
- the charge and discharge rate differ from the nominal capacity. • Suitable for parallel connection for all batteries. Serial connection are only suitable for 12V items with above 100AH capacity, and maximum four batteries. For 24V items.
- maximum two batteries are acceptable for serial connections.

Before connecting, bring to the same charge level. Batteries from different manufacturers or different types should not be interconnected.

Lithium LiFePo4 batteries are heavy. Make sure it is adequate and safe attach and always use the appropriate transport equipment. In an accident unsecured, batteries

could become a projectife! Always take carefully with lithium batteries. Make absolutely sure that the LiFePO4 battery is not connected with reversed polarity. Should the battery be connected incorrectly, the BMS ejectronics will be irreparably

damaged and must be replaced with a new BMS board. This is not a warranty case. The battery models LFP-12V40AHBL or LFP-12V80AHBL are Not designed in serial connections suitable! The battery model LFP-12V100AHBL or

LFP-12V150AHBL or LFP-12V200AHBL or LFP-12V300AHBL is acceptable for serial connection, max 4 batteries (48V). The battery model LFP-

24V50AHBL or LFP-24V100AHBL is acceptable for serial connections, max 2 batteries (48V). Series or parallel connections are only for the same standard battery. Disregard can lead to a defect!

Manual Instruction

Read the instruction manual carefully and make sure that you understand the contents before you use the product. When installing, using and maintaining the battery, the user safety must be guaranteed.

A lithium battery is required to achieve a stable power supply even under heavy loads, absolutely the best replacement for a lead acid battery. In addition to the extremely light weight advantage, it offers additional enormous energy reserves. Thanks to the ntegrated BMS (battery management system), SBL LiFePo4 batteries are for 12V DC or 24V DC applications. An increase in capacity through further LiFePo4 batteries can be easily implemented. The lithium iron phosphate battery is the safest of the regular lithium battery types. The nominal voltage of a LiFePO4 cell is 3.2V. A 12.8V LiFePO4 battery therefore consists of four cells connected in series and a 25.6V LiFePO4 battery consists of eight cells connected in series.

The battery is integrated Biuetooth. Biuetooth app can be loaded down by the look on "SBL Connect" (App Store or Google play).

it accepts parallel connections for increased capacity for all models and serial connections for increased voltage for some models (please refer to 1.3 technical data). Max serial connections four batteries for 12V series and max serial connections two batteries for 24V series (max. 48V).

RATTERY MANAGEMENT SYSTEM

The battery Management system (BMS) installed in every battery ensures that the battery in the event of under voltage or overload switches off and automatically again

turns on as soon as the problem is resolved. EASY REPLACEMENT THE EXISTING BATTERY

The dimensions of the housing are identical with the most common AGM, lead acid or GEL batteries. With optionally available round poles can also use existing pole, terminals can be reused. An exchange the battery holder or a change the loading structure is not

APPLICATION AREAS

The areas of application of this battery are specifically for the stationary or mobile area. Lithium batteries are diverse. Especially Mobile homes, solar, e-boats, electric scooters, golf carts or electron-mobiles / wheelchairs and cleaning machines will always be more often equipped with it.

BATTERY CHARGING

Use the suitable lithium battery charger. Waiting until the battery is fully charged. PERFORMANCE / EFFICIENCY

A SBL LiFeP34 battery can do more than 96% of the energy made available directly to save. A 100% utilization of the existing capacity takes place with the same output

1.1. PRODUCT FEATURES/ BENEFITS / AREAS OF APPLICATION

HIGH PERFORMANCE TRACTION / STORAGE BATTERY INTEGRATED (BMS) BATTERY MANAGEMENT SYSTEM HIGH CYCLES LIFE HIGH DISCHARGE CURRENT LIGHT WEIGHT ONE TO ONE REPLACEABLE WITH LEAD BATTERY

LOW SELF-DISCHARGE THE RIGHT BATTERY FOR EVERY APPLICATION

MOTORHOMES, CARAVANS
PHOTOVOLTAICS, SOLAR SYSTEMS AND RENEWABLE ENERGIES

HIGH PERFORMANCE TRACTION / STORAGE BATTERY FISHING, ELECTRIC BOAT MOTORS AND SONAR

MOBILE POWER SUPPLY, CAMPING AND LEISURE EMERGENCY POWER SUPPLY / UPS

1.2. BATTERYMANAGEMENT SYSTEM The battery management system (BMS) built into each battery ensures that the battery

switch off in the event of under voltage or overload and automatically again turns on as

off the charging process.

THE ADDITIONAL FUNCTIONS OF SBL BMS ARE: - Protection of the cell against under voltage by switching off the load in good time - Protection of the cell against over voltage by reducing the charging current or switching

Shutting down the system in the event of excess temperature.

- Charging of the battery is stopped in case of under temperature. 1.3. TECHNICAL DATA FOR LITHIUM LIFEPO4 BATTIERY WITH BLUETOOTH

Charge Voltage(V)
internal Impedance(mΩ)
Water Dust Resistance

Model

Nominal Voltage(V)

Nominal Capacity(Ah)

Usable Capacity(Wh)

Dimension (mm)

Charge Current(A)

Discharge Current(A)

Cycle Life

working Temperature (°C)

Discharge Voltage(V)

Charge Voltage(V)

Internal Impedatice(mQ)

Water Dust Resistance

Series or Parallel

LFP-12V80AHBL
12.8
80
1024
260*168*209
60
80
≥3000@25
- 20 ~ 60
12.8
14.6
≤20
IP65

Only Parallel

Model	LFP-12V100AHBL	LFP-12V150AHBL
Nominal Voltage(V)	12,8	12.8
Nominal Capacity(Ah)	100	150
Usable Capacity(Wh)	1280	1920
Dimension (mm)	278*175*190 330*172*215	330*172*215 355*175*190
Charge Current(A)	80	100
Discharge Current(A)	100	150
Cycle Life	≥5000@25	≥5000@25
Working Temperature (°C)	- 20 ~ 60	- 20 ~ 60
Discharge Voltage(V)	12.8	12.8
Charge Voltage(V)	14.5	14.6
internal Impedance(mΩ)	≤20	≤20
Water Dust Resistance	IP65	IP65
Series or Parallel connections	Both acceptable (max. 4)	Both acceptable (max.4)

LFP-12V40AHBL

12.8

512

198*166*170

>3000@25

- 20~60

12.8

14.6

≤20

IP65

Only Parallel

Model	LFP-12V200AHBL	LFP-12V300AHBI
Nominal voltage(v)	12.8	12.8
Nominal Capacity(Ah)	200	300
Usable Capacity(Wh)	2560	3840
Dimension (mm)	483*171*240 345*190*245	521*238*218
Charge Current(A)	150	150
Discharge Current(A)	200	200
Cycle Life	≥5000@25	≥5000@25
Working Temperature (°C)	- 20~60	- 30 ~ 60
Discharge Voltage(V)	12.8	12.8
Charge Voitage(V)	14.6	14.6
Internal Impedance(mΩ)	≤20	≤20
Water Dust Resistance	IP65	IP65
Series or Parallel connections	Both acceptable (max4)	Both acceptable (max.4)

Model	LFP-24V50AHBL	LFP:24V100.AHBI	
Nominal Voltage(V)	25.6	25.6	
Nominal Capacity(Ah)	50	100	
Usable Capacity(Wh)	1280	2560	
Dimension (mm)	260*168*209 278*175*190 330*172*214	345*190*245 483*171*240	
Charge Current(A)	30	80	
Discharge Current(A)	50	100	
Cycle Life	≥5000@25	≥5000@25	
Working Temperature (°C)	- 30~60	- 30 ~ 60	
Discharge Voitage(V)	25.6	25.6	
Charge Voltage('V)	29.2	29.2	
Internal Impédance(m·Ω)	≤20	≤20	
Water Dust Resistance	IP65	IP65	
Series or Parallel connections	Both acceptable (series max.2)	Both acceptable (series max. 2)	

2.5. IMPORTANTINSTRUCTIONS

Do not open the LiFePO4 battery without consulting the dealer. Unauthorized opening of

- the battery voids the manufacturer's warranty. • Only use the battery for the application for which it is intended.
- Do not short-circuit the LiFePO4 battery. The cable connections to the consumers
- must go through a backup to be protected. * Installation and maintenance may only be carried out by qualified specialists.
- Do not expose to permanent direct sunlight. Protect from the effects of heat. Temperatures above +60 ° C can damage the battery.
- Use only compatible chargers. The battery is in a longer storage of all
- disconnect devices.
- Pay attention to proper assembly. Avoid damage of any kind, for example by falling, drilling, etc. (Risk of short circuit).
- · Always keep the battery dry and clean.
- Note the plus (+) and minus (-) markings on the LiFePO4 battery and the device and pay attention to the correct polarity.
- The cycle capacity may vary due to the change in the working temperature and the charge and discharge rate differ from the nominal capacity.
- * Suitable for parallel connection and series connection and maximum four batteries for
- 12V series batteries and maximum two batteries for 24V series batteries. Before connecting, bring to the same charge level. Batteries from different

manufacturers or different types should not be inter 3. INSTALL THE BATTERY

Lithium LiFePo4 batteries are heavy. Make sure it is adequate and safe attach and always use the appropriate transport equipment. In an accident unsecured, batteries could become a projectile! Always take carefully with lithium batteries Make absolutely sure that the LiFePO4 battery is not connected with reversed polarity. Should the battery be connected incorrectly, the BMS electronics will be irreparably

damaged and must be replaced with a new BMS board. This is not a warranty case The battery model LFP-12V100AHBLH or LFP-12V150AHBLH or LFP-12V200AHBLH or LFP-12V300AHBLH is acceptable for serial connection, max 4 batteries (48V). The battery model LFP-24V50AHBLH or LFP-24V100AHBLH is acceptable for serial connections, max 2 batteries (48V). Series or parallel

Disregard can lead to a defect!

connections are only for the same standard battery.

Manual Instruction

Read the instruction manual carefully and make sure that you understand the contents before you use the product. When installing, using and maintaining the battery,

1. General information A lithium battery is required to achieve a stable power supply even under heavy loads,

absolutely the best replacement for a lead acid battery. In addition to the extremely light weight advantage, it offers additional enormous energy reserves. Thanks to the integrated BMS (battery management system), SBL LiFePo4 batteries are for 12V DC or 24V DC applications. An increase in capacity through further LiFePo4 batteries can be easily implemented. The lithium iron phosphate battery is the safest of the regular lithium battery types. The nominal voltage of a LiFePO4 cell is 3.2V. A 12.8V LiFePO4 battery therefore consists of four cells connected in series and a 25.6V LiFePO4 battery consists of eight cells connected in series.

The battery is integrated Bluetooth. Bluetooth app can be loaded down by the look on "SBL Connect" (App Store or Google play). It accepts parallel connections for increased capacity and serial connections for increased

voltage. Max serial connections four batteries for 12V series and max serial connections two batteries for 24V series (max. 48V). The battery consists of two energy-efficient heating elements coatrolled fully automatically by the BMS, which use the charging current to bring the cell temperature constantly above

BMS (BATTERY MANAGEMENT SYSTEM)

The Battery Management system (BMS) installed in every battery ensures that the battery in the event of under voltage or overload switches of and automatically again turns on as soon as the problem is resolved.

freezing point, thus guaranteeing maximum charging and discharging performance even at

EASY REPLACEMENT THE EXISTING BATTERY

The dimensions of the housing are identical with the most common AGM, lead acid or GEL batteries. With pottonally available round poles can also use existing pole, terminals can be reused. An exchange the battery holder or a change the loading structure is not

APPLICATION AREAS

The areas of application of this battery are specifically for the stationary or mobile area. Lithium batteries are diverse. Especially Mobile homes, solar, e-boats, electric scooters, golf carts or electron-mobiles / wheelchairs and cleaning machines will always be more often equipped with it.

Use the suitable lithium battery charger. Waiting until the battery is fully charged. PERFORMANCE / EFFICIENCY A SBL LiFePo4 battery can do more than 96% of the energy made available directly to

save. A 100% utilization of the existing capacity takes place with the same output

1.1. PRODUCT FEATURES / BENEFITS / AREAS OF APPLICATION HIGH PERFORMANCE TRACTION / STUTAGE BATTLERY

INTEGRATED (BMS) BATTERY MANAGEMENT SYSTEM SAFE LITHIUM TECHNOLOGY (LIFEPO4) HIGH CYCLES LIFE HIGH DISCHARGE CURRENT LIGHT WEIGHT ONE TO ONE REPLACEABLE WITH LEAD BATTERY LOW SELF-DISCHARGE

THE RIGHT BATTERY FOR EVERY APPLICATION MOTORHOMES, CARAVANS PHOTOVOLTAICS, SOLAR SYSTEMS AND RENEWABLE ENERGIES HIGH PERFORMANCE TRACTION / STURAGE BATTERY

FISHING, ELECTRIC BOAT MOTORS AND SONAR MOBILE POWER SUPPLY, CAMPING AND LEISURE EMERGENCY POWER SUPPLY / UPS

THE ADDITIONAL FUNCTIONS OF SBL BMS ARE:

1.2. BATTERY MANAGEMENT SYSTEM

off the charging process.

The battery management system (BMS) built into each battery ensures that the battery switch off in the event of under voltage or overload and automatically again turns on as

- Protection of the cell against under voltage by switching off the load in good time. - Protection of the cell against over voltage by reducing the charging current or switching

Shutting down the system in the event of excess temperature. - Charging the battery is stopped in case of under temperature

1.3. TECHNICAL DATA FOR LITHIUM UFEPO4 BATTERY WITH BLUETOOTHAND HEATING

Nominal Voltage(V)	25.6	25.6	12.8
Nominal Capacity(Ah)	50	100	100
Usable Capacky (Wh)	1280	2560	1280
Dimension (mm)	309*168*209 278*175*190 330*172*214	345*190*245 483*171*240	278*175*190 330*172*214 355*175*190
Charge Current(A)	30	80	80
Discharge Current(A)	50	100	100
Cycle Life	≥3000@25	≥5000@25	≥5000@25
Working Temperature ℃	- 30 ~ 60	- 30 ~ 60	- 30 ~ 60
Discharge Voltage(V)	25.6	25.6	12.8
Charge Voltage(V)	29.2	29.2	14.6
Internal Impedance (mΩ)	≤20	≤2 0	≤20
Water Dust	IP65	IP65	IP65

LFP-24V50AHBLH LFP-24V100AHBLH LFP-12V100AHBLH

Model	LFP-12V150AHBLH	LFP-12V200AHBLH	LFP-12V300AHBLH
Nomirial Voltage(V)	12.8	12.8	12.8
Nominal Capacity(Ah)	150	200	300
Usable Capacity (Wn)	1920	2560	3840
Dimension (mm)	330*172*214 355*175*190	345*190*245 483*171*240	521*238*218
Charge Current(A)	100	150	150
Discharge Current(A)	150	200	200
Cycle Life	≥5000@25	≥5000@25	≥5000@25
Working Temperature °C	- 30 ~ 60	- 30 ~ 60	- 30 ~ 60
Discharge Voltage(V)	12.8	12.8	12.8
Charge Voltage(V)	14.6	14.6	14.6
Internal Impedance (mΩ)	≤20	≤20	≤20
Water Dust Resistance	IP65	IP65	IP65
Series /Parallel connections	Both acceptable (max. 4)	Both acceptable (max. 4)	Both acceptable (max. 4)

2. SAFETY GUIDELINES AND MEASURES

PLEASE FOLLOW THESE INSTRUCTIONS AIND SAVE FOR FUTURE, LOOK AT NEAR TO THE LITHIUM LIFEPO4 BATTERY.

The battery may only be used for the purposes described in the operating instructions. Use for other purposes is considered improper use and has the invalidity of the result in product guarantee. The manufacturer is not liable for damage caused by faulty, improper use or improper use of the product. Use in aviation or in medical devices that serve to support life contradict the intended use. LiFePO4 Batteries are designed for use as energy storage. Possible areas of application for the battery are used as a service and on-board

battery in leisure vehicles or boat. 2.2. MARKINGS

CE Conformity mark (CE mark).

RoHS Conformity according to RoHS directive. MSDSConformity mark for material safety data sheet.

Fire, naked flames and smoking are prohibited! Sparking when handling avoid cables and short circuits.

Not waterproof.

Dispose of the Lithium Lif-ePO4 battery in accordance with your local, state, and local authority, federal laws and regulations. Batteries can be sent to the manufacturer, can be returned. Do not mix with other (industrial) waste.

This product or pants of this product can be recycled. The connections of the lithium battery are always live. Therefore, never place objects or

tools on the lithium battery. Avoid short circuits. Use isolated tools. Do not wear metallic objects such as watches, bracelets, etc. on your body. Use at a class D fire extinguisher, foam or CO2 fire extinguisher

2.3. STORAGE AND TRANSPORT INFORMATION The battery must be packed and protected well during transport.

The lithium battery must be transported according to the rules for transport, these should always be followed (transportation code UN3480/UN38.3).

Never lift the battery by the terminals, only by the handles. The battery should be stored in temperatures from -10 $^{\circ}\mathrm{C}$ to +40 $^{\circ}\mathrm{C}$. During transport, the battery should be about 50-60% charged.

The battery should be charged every three months to keep it active so that it always works maximum.

2.4. DISPOSAL

Batteries that are marked with the recycling symbol must be returned to approved recycling points. You can also contact the manufacturer by arrangement to be returned. Batteries must not be disposed of in household or industrial waste.